



Security Camera World

Security you can count on

SM7 - 4 zone audio surveillance kit



SM7 Price: \$360.95

Complete 4 zone, manual switching, audio surveillance system with built in speaker. Can be used independently for monitoring live audio or with DVRs for recording and playback. Two modes of operation: Switcher (select one of four zones) or mixer (select any combination of zones).

Kit Includes

- 4 SM1 Pre-amplified microphones.
- SM4 Switcher / mixer / amplifier.
- 12 VDC AC adapter.
- 3' Dual RCA Patch cable.
- Warning label.

Options

- SM1S surface mount adapter for SM1.
- White (standard) or ivory face plate.
- RM3 Rack mount.

Wiring Requirements

Stranded 22-gauge, 2-conductor shielded cable. Distances up to 1000'.

Caution

It may be against the law to install this equipment in certain environments. It is the responsibility of the installation company and end user to comply with state and federal laws. If you are unfamiliar with these laws, consult a qualified attorney.

It may be against the law to install this equipment in certain environments. It is the responsibility of the installation company and end user to comply with state and federal laws. If you are unfamiliar with these laws, consult a qualified attorney.

Warranty

1 year parts and labor.

SM1 Microphone Specifications

Omni-directional element w/25' range.
Low noise MOSFET preamplifier.
Line level, unbalanced output.
Adjustable gain.
Treble boost circuit. Selectable on/off.
Enhances clarity of time lapse recordings.
Limiter circuit. Selectable on/off.
Easy cable run termination.
Flush or surface mountable.
Power: 12 VDC @ 10mA.

SM4 Switcher / Mixer Specifications

In/out switches and level controls for each microphone channel.
Standard RCA jacks for connection to tape recorders, etc.
All settings stored in non-volatile memory.
1 Watt Power amplifier.
3" full range speaker.
Tape monitor switch.
3.5mm Headphone jack.
Power: 12 VDC @ 250mA
Reverse polarity protected and fused.
Dimensions W 5.57 x L 5.57 x H 1.52